SP-2

Call Point Protector


- Polycarbonate construction
- Surface mount
- · Can retro fit over existing device
- · Red and green covers supplied
- Built-in 96db sounder
- Supplied with Break Seal


Specification

- Protective cover helps prevent malicious or accidental false fire alarms
- Break seal option for added security
- Available with or without a 96dB integral sounder powered by a 3V lithium battery














Standby current: 15µA

Volume Low: 87dB@1m, 8mA High: 94dB@1m, 20mA

Battery Primary Lithium Battery 3v, 1500mAH

